

**NEW!**

# **CentaurSlam Hornet Emergency 18W+40W**

PORTABLE EX-CERTIFIED EMERGENCY WORK LIGHT

## **THE FIRST PORTABLE EMERGENCY EX LUMINAIRE**

- powerful lighting for dark conditions
- continued lighting despite power outages
- quicker and safer execution of temporary jobs

**Ex**



*Reliable illumination is crucial in jobs performed in hazardous atmospheres. Thanks to CentaurSlam Hornet Emergency, you're now able to carry out these expert tasks without delay.*



### SEE CHALLENGING JOBS IN A NEW LIGHT

Relieving news for tough jobs: Centaurea has developed the first portable industrial luminaire to facilitate expert jobs in hazardous spaces. CentaurSlam Hornet Emergency 18W+40W combines the latest features in explosion protection and emergency lighting.

CentaurSlam Hornet Emergency brings reliable lighting right where demanding

jobs take place. Thanks to its battery backing, the unit keeps exit routes illuminated even in power failures.

Designed and certified as portable equipment, the lighting innovation ensures uncompromised safety for temporary jobs. When plugged in, both the 18W and 40W lights are illuminated. In electricity cuts, the 18W fluorescent lamp remains lit for about one hour. What is more, it can be tailored to your specific application and site requirements.

### CENTAURSLAM HORNET EMERGENCY 18W+40W IS

- portable and battery-backed
- for use in hazardous areas, zones 1 & 21
- tough and durable
- versatile
- lightweight
- high light output
- linkable in series
- low maintenance need
- waterproof

### TECHNICAL DATA

<b>Certification:</b>	Ex II 2 GD Ex e ib mb IIB T3 Gb Ex t IIIC T90°C Db
<b>Ingress protection:</b>	IP66
<b>Operating temperature:</b>	-40°C – +40°C
<b>Supply voltage:</b>	24VAC/DC – 42VAC/ DC – 110VAC – 230VAC
<b>Power in normal conditions:</b>	18W + 40W
<b>Power during electricity cuts:</b>	18W (with 30% illumination)
<b>Battery operational during electricity cuts:</b>	approx. 1 hour
<b>Dimensions:</b>	1005mm x 115mm Ø
<b>Weight:</b>	3.7kg
<b>Variables:</b>	A (no in-built socket) B (cable in – cable out) C (with in-built socket)

Centaurea Oy

P.O. Box 89  
FIN-60101 Seinäjoki  
Finland

Tel. + 358 6 4212 400

Fax: + 358 6 4140 631

www.centaurea.fi

**CENTAUREA**

— Lighting the way to safe work —