

**NEW!**

# **CentaurSlam Trans 400EX**

PORTABLE EX-CERTIFIED TRANSFORMER



## **EX TRANSFORMER GOES TRULY PORTABLE**

- reliable power supply for hazardous conditions
- extreme shock and wear resistance
- safer and more flexible execution of temporary jobs





*Tightly scheduled jobs carried out in hazardous conditions depend on a flexible power supply. Besides improving safety, the portable CentaurSlam Trans 400EX makes your experts' jobs a lot easier.*



### BRING POWER WHEREVER YOU NEED IT

Industrial inspection, maintenance and construction are now safer than ever before – thanks to the first-ever portable transformer that Centaurea has developed for explosion-hazardous areas, including zone 1.s

CentaurSlam Trans 400EX meets all current safety requirements and electrical standards to the full. Its innovative design features supply voltage step-down

to ensure safety in confined spaces. With its shock-dissipating elastomer enclosure and highly wear-resistant surface materials, the unit represents new-generation durability in industrial transformers.

The CentaurSlam Trans 400EX certification covers the whole unit, and it is part of the CentaurSlam portable lighting range. For further convenience, the unit can be customized to your specifications.

### CENTAURSLAM TRANS 400EX

- a portable step-down transformer
- for use in hazardous areas, zones 1 & 21
- state-of-the-art design
- tough and durable
- linkable with portable CentaurSlam Hornet Ex lighting fixtures
- low maintenance need
- multiple socket outlet options

### TECHNICAL DATA

<b>Certification:</b>	CE0537 EX II GD Ex ed IIC T4 Gb (equipment certificate)
<b>Ingress protection:</b>	IP66
<b>Operating temperature:</b>	-20 °C – +40°C
<b>Supply voltage:</b>	110VAC – 230VAC
<b>Output voltages:</b>	24VAC – 48VAC
<b>Output current:</b>	11A
<b>Power:</b>	400VA
<b>Dimensions:</b>	500mm x 360mm x 300mm
<b>Weight:</b>	19kg (with 10m cable)
<b>Surface materials:</b>	Dissipative elastomer and aluminium
<b>Variables:</b>	Ex socket outlets 1-4 pcs (types upon request) Supply cable type and length upon request Plug upon request



Centaurea Oy

P.O. Box 89  
FIN-60101 Seinäjoki  
Finland  
Tel. + 358 6 4212 400  
Fax: + 358 6 4140 631  
www.centaurea.fi

**CENTAUREA**

— Lighting the way to safe work —

11/2008. The contents of this data sheet are subject to change without prior notice. Technical data for information purposes only.